

AV-15 Calibration

Note; There are no user adjustable components in the AV-15 design. The calibration is done yearly to insure that the unit is still functioning within specifications.

The following is performed during factory calibration;

Connect AV-15 output to a HP8568B (or equiv) spectrum analyzer using approx 3 ft RG58 coax. The analyzer must have a precision frequency standard that is accurate to $\pm 1 \times 10^{-7}$ Hz or better and 30Hz or less resolution BW.

General info;

Sideband to carrier db for double sideband AM=20 LOG(%AM/200)

DDM=((Large % - Small %)/100)

ILS Localizer;

Set the HP8568B center freq to 108.1 and span to 2KHz. Select ILS localizer 108.1 and DDM=0 (CENTER) on the AV-15. Check that; Frequency=108.1MHz (± 2.5 PPM ± 1 PPM aging per year) and that the power is -12dbm (± 6 dbm).

With the center selected, check that the 90Hz and 150Hz sidebands are equal (± 1 db) and -20db (± 1 db) from carrier.

Set 1/2 right on AV-15. Side bands -18.5 (± 1) db and -21.9 (± 1) db

Set Full right on AV-15 Side bands -17.2 (± 1) db and -24.2 (± 1) db

Set 150 Hz OFF and see that sideband gone.

Set 90 Hz OFF and see that sideband gone.

ILS Glide slope;

Change the HP8568b to 334.7MHz 2KHz scan and check the AV-15 glide slope signal for frequency accuracy ± 2.5 PPM \pm aging, power=-17dbm ± 6 dbm, 90Hz and 150Hz AM mod sidebands -14dbm ± 2 db from carrier and ± 1 db of equal magnitude for center.

For 1/2 the sidebands should be -13.1(± 1) and -15(± 1) db down.

For FULL the sidebands should be -12.25(± 1) and -16.125(± 1) db down.

Set 150 Hz OFF and see that sideband gone.

Set 90 Hz OFF and see that sideband gone.

ILS Marker;

Check for 75MHz ± 5 ppm carrier with -15dbm ± 3 db power out. check on/off AM mod as;

outer marker 400Hz $\pm 5\%$

middle marker 1300Hz $\pm 5\%$

inner marker 3000Hz $\pm 5\%$

VOR;

Select VOR mode and 108 MHz freq on AV-15. Measure the center frequency and power.

108MHz ± 2.5 PPM aging and -10dbm ± 3 dbm in 10KHz analyzer BW.

Using a modulation analyzer check that the 30Hz AM and 9960Hz subcarrier provide about 30% AM and that the on/off 1024Hz tone is giving about 10% AM mod. Check the Phase between the two 30Hz signals to insure they are within ± 1 degree of expected phase.

Check the other VOR frequencies and their power.

DME;

Use a 1GHz bandwidth Tek-7104 scope (or equiv). View the AV-15 output signal. The output will be pulse pairs spaced 12uS +/- .1uS for the 108.0 X mode and 36uS +/- .1uS for the 108.05 Y mode. The output power =-12dbm +/- 6dbm. Check the AV-15 with a known good DME for proper lock.

ADF;

Use the spectrum analyzer to check the ADF am signals. Freq within +/- 5ppm and output power -15dbm +/- 6dbm. On/off AM modulation.

Transponder;

Using the 1GHZ bandwidth above, scope view the AV-15 output and check power for -15dbm +/-6dbm. The HP8568B analyzer can be used to check the carrier frequency by selecting the AV-15 MODE-A squawk mode and using the appropriate analyzer scan rate to determine the aprox output frequency.

COMM;

Using an accurate digital frequency counter, measure the communications output frequencies.

Using an accurate frequency source at 0dbm power, measure its frequency with the AV15 to check for +/- 2PPM +/- generator accuracy when the difference frequency is 1000Hz.

Finally all the transponder modes are checked using a known good mode-a/c/s-ES transponder.

If any of the above tests fail the factory should be contacted for repair.